




Agenda

- Overview of WAN Issues
- Network Interfaces—Routed WAN
- Router Tools and Concepts
- Network Interfaces—Switched WAN
- Switch Tools and Concepts


www.cisco.com

The WAN Network




The WAN Network (Cont.)

WAN Speeds



www.cisco.com

The WAN Network (Cont.)



www.cisco.com

Network Interfaces

- **Customer premise side**

Routers i.e., Cisco 7500, 7200, 2600, 3810

DCE i.e., CSUs, DSUs, modems

www.cisco.com

Network Interfaces (Cont.)

- **Network provider side**

Switches: i.e., ATM, ISDN, Frame

MUX: i.e., DACs, SONET, channel banks

www.cisco.com

Network Interfaces (Cont.)

- **Key configuration concerns**
 - Clocking**—network synchronization
 - Framing**—ESF, M23, cbit
 - Coding**—B8ZS, B3ZS

www.cisco.com

Network Interfaces (Cont.)

- **Red alarm**
 - Loss of signal(LOS) or out of frame (OOF) on RX
- **Yellow alarm**
 - Signal that far end has loss of RX. Sometimes known as Remote Alarm Indication(RAI)
- **Blue alarm**
 - Loss of signal upstream. Known as Alarm Indication Signal(AIS)

www.cisco.com

Network Interfaces (Cont.)

- **Clocking concerns**

Synchronize network elements

Clock sources—highest quality

Design for resiliency

www.cisco.com

Network Interfaces (Cont.)

- **Stratum levels of accuracy**

- **Stratum 1** source is usually an atomic standard

Stratum 1 drives strata 2-3-4

1×10^{-11} (BSRF*) (± 1 second in 3170 years!)

- **Stratum 2** drives strata 2-3-4 clocks

1.5×10^{-10} (15 times worse than BSRF) (± 1 second in 5.07 years)

- **Stratum 3** drives strata 3-4 clocks

4.6×10^{-6} (460,000 times worse than BSRF) (± 1 second in 51.6 days)

- **Stratum 4** should never be used as source to any clock system

3.2×10^{-5} (3,200,000 times worse than BSRF) (± 1 second in 3.68 days)

BSRF = Bell System reference frequency

www.cisco.com

Network Interfaces for Routed WAN

- Router platforms with internal DSU/CSU

Cisco 3810 with MultiFlex Trunk (MFT)

Cisco 2600 and 3600 WAN Interface Card (WIC)

www.cisco.com

Network Interfaces for Routed WAN (Cont.)

Router Commands

wan-3810a(config)#controller e1 0

Controller configuration commands:

cablelength	Specify the cable length for a DS1 link
channel-group	Specify the timeslots to channel-group mapping for an interface
clock	Specify the clock source for a DS1 link
default	Set a command to its defaults
description	Controller specific description
exit	Exit from controller configuration mode
fdl	Specify the FDL standard for a DS1 data link
framing	Specify the type of Framing on a E1 link
linecode	Specify the line encoding method for a E1 link
loop-detect	Loopback up or down detection
loopback	Put the entire E1 line into loopback
mode	Configure the controller mode
pri-group	Configure the specified timeslots for PRI
shutdown	Shut down a E1 link (send Blue Alarm)
tdm-group	Configure DS0 group for TDM

www.cisco.com

Network Interfaces for Routed WAN (Cont.)

Show Controller [E1|T1]

```
wan-3810a#sh cont e1 0
E1 0 is down.
  Applique type is Channelized E1 - balanced
  Transmitter is sending remote alarm.
  Receiver has loss of signal.
  Slot 3 Serial #09034728 Model TEB HWVersion 4.70 RX level = 35DB
  Framing is CRC4, Line Code is HDB3, Clock Source is Line.
  Data in current interval (867 seconds elapsed):
    8862 Line Code Violations, 0 Path Code Violations
    0 Slip Secs, 0 Fr Loss Secs, 867 Line Err Secs, 0 Degraded Mins
    0 Errored Secs, 0 Bursty Err Secs, 0 Severely Err Secs, 867 Unavail Secs
  Data in Interval 1:
    6373 Line Code Violations, 0 Path Code Violations
    0 Slip Secs, 0 Fr Loss Secs, 897 Line Err Secs, 0 Degraded Mins
    0 Errored Secs, 0 Bursty Err Secs, 0 Severely Err Secs, 900 Unavail Secs
  Data in Interval 2:
    7404 Line Code Violations, 0 Path Code Violations
    0 Slip Secs, 0 Fr Loss Secs, 898 Line Err Secs, 0 Degraded Mins
    0 Errored Secs, 0 Bursty Err Secs, 0 Severely Err Secs, 900 Unavail Secs
```

www.cisco.com

Network Interfaces for Routed WAN (Cont.)

Router Commands

```
wan-2524(config-if)#service-module t1?
clock                Service module clock source
data-coding          Service module DCE line coding
fdl                  Specify the FDL standard for a DS1 data
framing              Framing format
lbo                  Line Build Out format
linecode             Line coding format
remote-alarm-enable  Remote/Yellow alarm enable
remote-loopback      Remote Loopback/RL disable
timeslots            Fraction timeslots
```

www.cisco.com

Network Interfaces for Routed WAN (Cont.)

Show Service Module

```
wan-2524#sh service-module
Module type is T1/fractional
  Hardware revision is B, Software revision is 1.2 ,
  Image checksum is 0x2162E11, Protocol revision is 1.1
Receiver has no alarms.
Framing is ESF, Line Code is B8ZS, Current clock source is line
Fraction has 24 timeslots (64 Kbits/sec each), Net bandwidth is 1536 Kbits/sec.
Last user loopback performed:
  dte loopback
  duration 00:00:48
Last module self-test (done 04:46:18): Passed
Last clearing of alarm counters 2w2d
  loss of signal      : 4, last occurred 04:20:53
  loss of frame      : 4, last occurred 00:18:01
  AIS alarm          : 1, last occurred 04:37:55
  Remote alarm       : 0,
  Module access errors : 0,
Total Data (last 96 15 minute intervals):
  65537 Line Code Violations, 4 Path Code Violations
  0 Slip Secs, 439 Fr Loss Secs, 387 Line Err Secs, 0 Degraded Mins
  4 Errored Secs, 0 Bursty Err Secs, 4 Severely Err Secs, 439 Unavail Secs
Data in current interval (498 seconds elapsed):
  0 Line Code Violations, 0 Path Code Violations
  0 Slip Secs, 0 Fr Loss Secs, 0 Line Err Secs, 0 Degraded Mins
  0 Errored Secs, 0 Bursty Err Secs, 0 Severely Err Secs, 0 Unavail Secs
```

www.cisco.com

Network Interfaces for Routed WAN (Cont.)

- **VIP-based WAN interfaces**

PA-T4

PA-CT3

MC-T3

MC-T1

PA-POS

www.cisco.com

Network Interfaces for Routed WAN (Cont.)

```
Router# sh int serial 1/0
Serial1/0 is up, line protocol is up
Hardware is M4T
Internet address is 10.10.10.1
MTU 1500 bytes, BW 1544 Kbit, DLY 20000 usec, rely 255/255, load 1/255
Encapsulation PPP, loopback not set, keepalive set (10 sec)
LCP Open
Open: ipcp
Last input 00:00:09, output 00:00:09, output hang never
Last clearing of "show interface" counters never
Input queue: 0/75/0 (size/max/drops); Total output drops: 0
Queueing strategy: weighted fair
Output queue: 0/64/0 (size/threshold/drops)
  Conversations 0/1 (active/max active)
  Reserved Conversations 0/0 (allocated/max allocated)
5 minute input rate 0 bits/sec, 0 packets/sec
5 minute output rate 0 bits/sec, 0 packets/sec
1675 packets input, 26792 bytes, 0 no buffer
Received 0 broadcasts, 0 runts, 0 giants
0 input errors, 0 CRC, 0 frame, 0 overrun, 0 ignored, 0 abort
1676 packets output, 26806 bytes, 0 underruns
0 output errors, 0 collisions, 0 interface resets
0 output buffer failures, 0 output buffers swapped out
0 carrier transitions  DCD=up DSR=up DTR=up RTS=up CTS=up
```

www.cisco.com

Network Interfaces for Routed WAN (Cont.)

T1 Controller Configs

```
wan-7204a(config)#controller t1 3/0
```

Controller configuration commands:

bert	Start BERT test
cablelength	Specify the cable length for a DS1 link
channel-group	Specify the timeslots to channel-group mapping for an interface
clock	Specify the clock source for a DS1 link
description	Controller specific description
exit	Exit from controller configuration mode
fdl	Specify the FDL standard for a DS1 data link
framing	Specify the type of Framing on a DS1 link
linecode	Specify the line encoding method for a DS1 link
loopback	Put the entire T1 line into loopback
no	Negate a command or set its defaults
pri-group	Configure the specified timeslots for PRI
shutdown	Shut down a DS1 link (send Blue Alarm)

www.cisco.com

Network Interfaces for Routed WAN (Cont.)

```
Router# show controllers t1 3/0
```

T1 1/0 is up.

No alarms detected.

Framing is **ESF**, Line Code is **B8ZS**, Clock Source is **Line**.

Data in current interval (710 seconds elapsed):

0 Line Code Violations, 0 Path Code Violations

0 Slip Secs, 0 Fr Loss Secs, 0 Line Err Secs, 0 Degraded Mins

0 Errored Secs, 0 Bursty Err Secs, 0 Severely Err Secs, Unavail,Secs

Data in Interval 1:

0 Line Code Violations, 0 Path Code Violations

0 Slip Secs, 0 Fr Loss Secs, 0 Line Err Secs, 0 Degraded Mins

0 Errored Secs, 0 Bursty Err Secs, 0 Severely Err Secs, 0 Unavail Secs

www.cisco.com

Network Interfaces for Routed WAN (Cont.)

T3 Controller Configs

```
wan-7204a(config)#controller t3 1/0
```

Controller configuration commands:

cablelength	cable length in feet (0-450)
clock	Specify the clock source for a T3 link
description	Controller specific description
framing	Specify the type of Framing on a T3 link
idle	Specify the idle pattern all channels on a T3 interface
loopback	Put the entire T3 line into loopback
mdl	Maintenance Data Link Configuration
no	Negate a command or set its defaults
shutdown	Shut down a DS3 link (send DS3 Idle)
t1	Create a T1 channel

www.cisco.com

Network Interfaces for Routed WAN (Cont.)

MC-T3 Config

Controller T3 1/0

Clock source line

Cablelength 20

T1 1 channel-group 0 timeslots 1-24

T1 1 clock source line

www.cisco.com

Network Interfaces for Routed WAN (Cont.)

Show Controller T3

```
wan-7204a#sh cont t3
T3 1/0 is up. Hardware is CT3 single wide port adapter
CT3 H/W Version : 1.0.1, CT3 ROM Version : 1.1, CT3 F/W Version : 2.1.1
FREEDM version: 1, reset 0
Applique type is Channelized T3
Description:
No alarms detected.
FEAC code received: No code is being received
Framing is M23, Line Code is B3ZS, Clock Source is Line
Rx throttle total 0
Data in current interval (55 seconds elapsed):
  0 Line Code Violations, 0 P-bit Coding Violation
  0 C-bit Coding Violation, 0 P-bit Err Secs
  0 P-bit Severely Err Secs, 0 Severely Err Framing Secs
  0 Unavailable Secs, 0 Line Errored Secs
  0 C-bit Errored Secs, 0 C-bit Severely Errored Secs
Total Data (last 6 15 minute intervals):
  0 Line Code Violations, 0 P-bit Coding Violation,
  0 C-bit Coding Violation, 0 P-bit Err Secs,
  0 P-bit Severely Err Secs, 0 Severely Err Framing Secs,
  0 Unavailable Secs, 0 Line Errored Secs,
  0 C-bit Errored Secs, 0 C-bit Severely Errored Secs
```

www.cisco.com

Network Interfaces for Routed WAN (Cont.)

Show Controller T3 (Cont.)

```
T1 1 is up
timeslots: 1-24
FDL per AT&T 54016 spec.
No alarms detected.
Framing is ESF, Clock Source is Line
Data in current interval (73 seconds elapsed):
  0 Line Code Violations, 0 Path Code Violations
  0 Slip Secs, 0 Fr Loss Secs, 0 Line Err Secs, 0 Degraded Mins
  0 Errored Secs, 0 Bursty Err Secs, 0 Severely Err Secs
  0 Unavail Secs, 0 Stuffed Secs
Total Data (last 6 15 minute intervals):
  0 Line Code Violations, 0 Path Code Violations,
  0 Slip Secs, 0 Fr Loss Secs, 0 Line Err Secs, 0 Degraded Mins,
  0 Errored Secs, 0 Bursty Err Secs, 0 Severely Err Secs
  8 Unavail Secs, 0 Stuffed Secs
T1 2 is down.....
T1 3 is down.....
T1 4 is down.....etc
```

www.cisco.com

Network Interfaces for Routed WAN (Cont.)

POS Interfaces

- Configuration issues

A few items need to be known before configuring Cisco routers to support SONET; Also, depending on the specific controller type and network operations, **not** all of the items listed below may be supported or required

Clock source—line or internal—specifies whether the clock is obtained from the line signal or from the internal oscillator; clock source may be set to line if router connects to a SONET/SDH ADM or set to internal if it connects to another router; (note: the internal clock will always be used to transmit an AIS alarm signal if there is an incoming LOS)

Framing—SONET or SDH—selects whether STS or STM framing is used; (may be fixed if controller does not support both)

www.cisco.com

Network Interfaces for Routed WAN (Cont.)

POS Interfaces


- **Payload scramble**—on or off—normally on (sometimes this is not configurable in the controller, in which case scrambling will always be on)
- **Alarm reporting**—specify which alarms are to be reported; select none or all of items such as: b1-tca, b2-tca, sf-ber, sd-ber, los, lof, ais-l and rdi-l
- **Alarm thresholds**—specify the BER thresholds which will cause an alarm report for: b1-tca, b2-tca, sf-ber and sd-ber

www.cisco.com

Network Interfaces for Routed WAN (Cont.)

```
router# show controller pos 2/0/0
POS2/0/0
SECTION
  LOP = 0      LOS = 2      BIP(B1) = 0
LINE
  AIS = 2     RDI = 20     FEBE = 0     BIP(B2) = 0
PATH
  AIS = 2     RDI = 2     FEBE = 0     BIP(B3) = 0
  LOP = 0     NEWPTR = 0   PSE = 0     NSE = 0
Active Defects: B2-TCA B3-TCA
Active Alarms: None
Alarm reporting enabled for: B1-TCA
APS
COAPS = 12612784  PSBF = 8339
State: PSBF_state = False
Rx(K1/K2): 00/CC Tx(K1/K2): 00/00
S1S0 = 03, C2 = 96
CLOCK RECOVERY -----trying to recover
RDOOL = 2
State: RDOOL_state = True
PATH TRACE BUFFER: UNSTABLE
Remote hostname :
Remote interface:
Remote IP addr  :
Remote Rx(K1/K2): .. Tx(K1/K2): ..
BER thresholds: SF = 10e-3 SD = 10e-8
TCA thresholds: B1 = 10e-7 B2 = 10e-3 B3 = 10e-6
```


www.cisco.com



Troubleshooting Tools— Loopbacks

56k CSU/DSU Loopback Line
T1 CSU/DSU Loopback Line


Router(config-if)# loopback line



Troubleshooting Tools— Loopbacks (Cont.)

56k CSU/DSU Loopback Line Payload
T1 CSU/DSU Loopback Line Payload

Router (config-if)# loopback line payload




Troubleshooting Tools— Loopbacks (Cont.)

56K CSU/DSU Module DTE Loop

T1 CSU/DSU Module DTE Loop


Router (config-if)# loopback dte



Troubleshooting Tools— Loopbacks (Cont.)

Far End Remote Loop

Router(config-if)# loopback remote full
other type loops- payload, smart-jack



Tools BERT

- Using the BER Test

```
t1 bert pattern {2^11 | 2^15 | 2^20 0.153 | 2^20 QRSS | 2^23 |  
0s |  
1s | alt-0-1} interval minutes
```

```
wan-7204a(config-controller)#bert pattern 0s int 5  
wan-7204a(config-controller)#no bert
```

```
5d02h: %LINK-6-BERTSTATUS: Interface T1 3/0, BERT is  
completed.
```

www.cisco.com

Troubleshooting Tools BERT

```
Router# sh cont t1 0/0/0 b
```

```
T1 0/0/0 is up.
```

```
DSX1 BERT pattern      : zeros  
DSX1 BERT sync         : sync  
DSX1 BERT sync count   : 1  
DSX1 BERT interval     : 2  
DSX1 BERT time remain  : 2  
DSX1 BERT total errs   : 0  
DSX1 BERT total k bits : 43155  
DSX1 BERT errors (last) : 0  
DSX1 BERT k bits (last) : 43155
```

```
Applique type is Channelized T1
```

```
No alarms detected.
```

```
Cablelength is long gain36 0db
```

```
Framing is ESF, Line Code is B8ZS, Clock Source is Line.
```

```
Data in current interval (24 seconds elapsed):
```

```
0 Line Code Violations, 0 Path Code Violations  
0 Slip Secs, 0 Fr Loss Secs, 0 Line Err Secs, 0 Degraded Mins  
0 Errored Secs, 0 Bursty Err Secs, 0 Severely Err Secs, 0 Unavail Secs
```

www.cisco.com

Troubleshooting Tools— Loopbacks (Cont.)

The POSIP “line” will be “up” when SONET/SDH frames are received. The POSIP “line protocol” will be “up” when the SONET/SDH frames convey information that is recognizable by the POSIP as data

Two “loop” commands are useful in diagnosing the origin of difficulty

1. “loop internal”—all Tx frames/data are “looped” internally within the POSIP; no data is sent on the outside; this is often helpful in the diagnosis of “clocking” issue; when looped internally, both “line” and “line protocol” will be “up” and the unit should be able to “ping” its own interface and handle keepalives
2. “loop line”—all Rx data on the inbound fiber is looped to the Tx side and re-transmitted; this is often helpful in the diagnosis of an intervening SONET/SDH infrastructure in an end-to-end troubleshoot exercise

www.cisco.com

Troubleshooting Tools BERT (Cont.)

```
POS(config-if)#bert pattern 2^23 interval 10
```

```
POS#show controller oc12 4/0:1
```

```
POS#show controller oc12 4/0:2 bert
```

```
POS(config-if)#bert errors 5
```

www.cisco.com

Troubleshooting Tools BERT (Cont.)

```
router#show controller oc12 4/0:2 bert
Interface Serial4/0 : 2 (DS3 channel 2)
BERT information:
State : enabled (not sync'd)
Pattern : 2^15
Interval : 10 minutes
Time remaining : 00:09:50
Total errors : 0
Time this sync : 00:00:00
Errors this sync : 0
Sync count : 0
```

www.cisco.com



WAN Connections

www.cisco.com

WAN Connections—Router

- **Frame Relay**
- **ATM**

www.cisco.com

WAN Connections Frame Relay

- **Verify physical connections**
 - Use router loops and network loops**
 - Run ping test using HDLC protocol**
 - Proper cabling**

www.cisco.com

WAN Connections Frame Relay (Cont.)

- Verify configuration
 - LMI type
 - Encapsulation type
 - Display show and debugs

www.cisco.com

WAN Connections Frame Relay (Cont.)

```
Serial0 is up, line protocol is down
Hardware is HD64570
MTU 1500 bytes, BW 1544 Kbit, DLY 20000 usec,
  reliability 255/255, txload 1/255, rxload 1/255
Encapsulation FRAME-RELAY, loopback not set, keepalive set (10 sec)
LMI enq sent 67458, LMI stat rcvd 0, LMI upd rcvd 0, DTE LMI down
LMI enq rcvd 17, LMI stat sent 0, LMI upd sent 0
LMI DLCI 1023 LMI type is CISCO frame relay DTE
FR SVC disabled, LAPF state down
Broadcast queue 0/64, broadcasts sent/dropped 33654/0, interface broadcasts 22439
Last input 00:00:32, output 00:00:00, output hang never
Last clearing of "show interface" counters never
Input queue: 0/75/0 (size/max/drops); Total output drops: 0
Queueing strategy: priority-list 8
Output queue (queue priority: size/max/drops):
  high: 0/20/0, medium: 0/40/0, normal 0/60/0, low 0/80/0
5 minute input rate 0 bits/sec, 0 packets/sec
5 minute output rate 0 bits/sec, 0 packets/sec
34044 packets input, 4008077 bytes, 0 no buffer
Received 0 broadcasts, 0 runts, 0 giants, 0 throttles
0 input errors, 0 CRC, 0 frame, 0 overrun, 0 ignored, 0 abort
34211 packets output, 4139097 bytes, 0 underruns
0 output errors, 0 collisions, 60 interface resets
0 output buffer failures, 0 output buffers swapped out
78 carrier transitions
DCD=up DSR=up DTR=up RTS=up CTS=up
```

www.cisco.com

WAN Connections Frame Relay (Cont.)

show frame pvc

PVC Statistics for interface Serial0 (Frame Relay DTE)

DLCI = 980, DLCI USAGE = LOCAL, PVC STATUS = ACTIVE,
INTERFACE = Serial0

input pkts 19	output pkts 87	in bytes 2787
out bytes 21005	dropped pkts 0	in FECN pkts 0
in BECN pkts 0	out FECN pkts 0	out BECN pkts 0
in DE pkts 0	out DE pkts 0	

pvc create time 1:17:47 last time pvc status changed 0:58:27

show frame map

Serial0 (up): ip 157.147.3.65 dlci 980(0x3D4,0xF440), dynamic,
broadcast, status defined, active

www.cisco.com

WAN Connections Frame Relay (Cont.)

Debug frame lmi

```
*Mar 1 01:17:58.763: Serial0(out): StEnq, myseq 92, yourseen 64, DTE up
*Mar 1 01:17:58.763: datagramstart = 0x20007C, datagramsize = 14
*Mar 1 01:17:58.763: FR encap = 0x0001030800 75 95 01 01 01 03 02 5C 40
*Mar 1 01:17:58.767:
*Mar 1 01:17:58.815: Serial0(in): Status, myseq 92
*Mar 1 01:17:58.815: RT IE 1, length 1, type 1
*Mar 1 01:17:58.815: KA IE 3, length 2, yourseq 65 myseq 92
*Mar 1 01:18:08.763: Serial0(out): StEnq, myseq 93, yourseen 65, DTE up
*Mar 1 01:18:08.763: datagramstart = 0x20007C, datagramsize = 14
*Mar 1 01:18:08.763: FR encap = 0x0001030800 75 95 01 01 01 03 02 5D 41
*Mar 1 01:18:08.767:
*Mar 1 01:18:08.815: Serial0(in): Status, myseq 93
*Mar 1 01:18:08.815: RT IE 1, length 1, type 1
*Mar 1 01:18:08.815: KA IE 3, length 2, yourseq 66, myseq 93
*Mar 1 01:18:18.763: Serial0(out): StEnq, myseq 94, yourseen 66, DTE up
*Mar 1 01:18:18.763: datagramstart = 0x20007C, datagramsize = 14
*Mar 1 01:18:18.763: FR encap = 0x0001030800 75 95 01 01 00 03 02 5E 42
*Mar 1 01:18:18.767:
*Mar 1 01:18:18.815: Serial0(in): Status, myseq 94
*Mar 1 01:18:18.815: RT IE 1, length 1, type 0
*Mar 1 01:18:18.819: KA IE 3, length 2, yourseq 67, myseq 94
*Mar 1 01:18:18.819: PVC IE 0x7 , length 0x3 , dlci 980, status 0x2
```

www.cisco.com

WAN Connections—ATM

- **ATM interface troubleshooting switch to router**

Interface remains down or intermittent transitions

Show interface

Show controller atm x/y/z

Cable, clocking, configuration

www.cisco.com

WAN Connections—ATM (Cont.)

- **ATM interface **up** state but traffic doesn't go through**

Show controller/interface atm—
look for errors

Check scrambling options

Run loopbacks

Router(config-if)# loopback plim

Show atm vc interface

www.cisco.com

WAN Connections—ATM (Cont.)

Make sure the other end is up and is not reporting any kind of yellow alarm (even though your end may be up); if it is, something is wrong between our TX and their RX path

- **Show atm vc traffic**

Check the cell counts; as long as you have some non-zero tx and rx cell counts, it is probably not an interface problem; if they are all 0

www.cisco.com

WAN Connections—ATM (Cont.)

- **Router# show atm traffic**

4915 input packets

2114 output packets

2913 broadcast packets

0 packets for nonexistent VC

0 packets with CRC errors

0 OAM cells received

0 cells lost

www.cisco.com

WAN Connections—ATM (Cont.)

Show Controller ATM

```
LS1010#show controller atm 11/1/1
IF Name ATM11/1/1  Chip Base Address A8D0A000
Port type OC3  Port rate 155 Mbps  Port medium Unknown
Port status SECTION LOS  Loopback None  Flags8300
TX Led Traffic Pattern  RX Led Traffic Patter
TX clock source network-derived
Framing mode sts-3c
Cell payload scrambling on
Sts-stream scrambling on

OC3 counters

Key txccl - # cells transmitted
rxcell - # cells received
b2 - # line BIP-8 errors
b3 - # path BIP-8 errors
ocd - # out-of-cell delineation errors - not implemented
g1 - # path FEBE errors
chcs - # correctable HEC errors
uhcs - # uncorrectable HEC errors
```

www.cisco.com

WAN Connections—ATM (Cont.)

```
LS1010# show atm vc 0/5
```

```
ATM0: VCD: 2, VPI: 0, VCI: 5, Connection Name: SAAL
UBR, PeakRate: 56
AAL5-SAAL, etype:0x4, Flags: 0x26, VCmode: 0x0
OAM frequency: 0 second(s), OAM retry frequency: 1 second(s), OAM retry frequency: 1 second(s)
OAM up retry count: 3, OAM down retry count: 5
OAM Loopback status: OAM Disabled
OAM VC state: Not Managed
ILMI VC state: Not Managed
ILARP DISABLED
InPkts: 2044, OutPkts: 2064, InBytes: 20412, OutBytes: 20580
InPRoc: 2044, OutPRoc: 2064, Broadcasts: 0
InFast: 0, OutFast: 0, InAS: 0, OutAS: 0
OAM cells received: 0
F5 InEndloop: 0, F5 InSegloop: 0, F5 InAIS: 0, F5 InRDI: 0
F4 InEndloop: 0, F4 InSegloop: 0, F4 InAIS: 0, F4 InRDI: 0
OAM cells sent: 0
F5 OutEndloop: 0, F5 OutSegloop: 0, F5 OutRDI: 0
F4 OutEndloop: 0, F4 OutSegloop: 0, F4 OutRDI: 0
OAM cell drops: 0
Compress: Disabled
Status: INACTIVE, State: NOT_IN_SERVICE
```

www.cisco.com

WAN Connections—ATM (Cont.)

```
router# show atm-vc 4
```

```
ATM3/0/0.30: VCD: 30, VPI: 0, VCI: 60, etype:0x0, AAL5 - LLC/SNAP, Flags: 0xC3
```

```
PeakRate: 44209, Average Rate: 0, Burst Cells: 0, VCmode: 0x0
```

```
OAM DISABLED, InARP frequency: 1 minute(s)
```

```
InPkts: 0, OutPkts: 0, InBytes: 0, OutBytes: 0
```

```
InPRoc: 0, OutPRoc: 0, Broadcasts: 0
```

```
InFast: 0, OutFast: 0, InAS: 0, OutAS: 0
```

```
InPktDrops: 0, OutPktDrops: 0
```

```
CrcErrors: 0, SarTimeOuts: 0, OverSizedSDUs: 0
```

```
OAM F5 cells sent: 0, OAM cells received: 0
```

```
Status: ACTIVE
```

```
ATM4/0: VCD: 4, VPI: 4, VCI: 4, etype:0xBAD, AAL5 - MUX, Flags: 0x34
```

```
PeakRate: 0, Average Rate: 0, Burst: 0 *32cells
```

```
InPkts: 164, OutPkts: 0, InFast: 0, OutFast: 0, Broadcasts: 0
```

www.cisco.com

WAN Connections—ATM (Cont.)

- OC-3—specific

Sonet PHY layer [sts-3c|stm-1]

Clock-source [free-running|network-derived|loop-timed]

Scrambling [sts-stream|cell-payload]

Loopback [line|diagnostic]

www.cisco.com

WAN Connections—ATM (Cont.)

- **OC-12—specific**

SONET PHY	[sts-12c stm-4]
Clock-source	[free-running network-derived]
Scrambling	[sts-stream cell-payload]
Loopback	[line diagnostic]

If there are repeaters in between, make sure they put out the right format of signal, i.e. STS-12c, rather than STS-12

www.cisco.com

WAN Connections—ATM (Cont.)

- **DS3—specific**

Framing [m23adm|cbitadm|m23plcp|cbitplcp]
lbo [short|long]—default is short (i.e. less than 225 feet)
Clock-source [free-running|loop-timed|network-derived]
Scrambling [cell-payload]—default is disabled
Loopback [line|diagnostic|cell|payload]
Autoferf [los|oof|red|ais|lcd]—default is monitor all

www.cisco.com



WAN Switch Interfaces

www.cisco.com


Network Interface Switched WAN

- **Cisco MGX™ 8220**
 - Lines, ports, channels
 - Frame Relay Service Modules—FRSM
 - ATM UNI Service Modules—AUSM

www.cisco.com

Network Interface Switched WAN (Cont.)

Line Definition



Network Interface Switched WAN (Cont.)

Display Lines

MGX1.1.7.FRSM.a > dsplns

Line Type	Conn Type	Type	Status/Coding Source	Length	XmtClock Alarm	Alarm	Stats
7.1	DB-15	dsx1ESF	Mod/dsx1B8ZS	0-110 ft	LocalTim	No	No
7.2	DB-15	dsx1ESF	Ena/dsx1B8ZS	0-110 ft	LocalTim	Yes	No
7.3	DB-15	dsx1ESF	Mod/dsx1B8ZS	0-110 ft	LocalTim	Yes	No
7.4	DB-15	dsx1ESF	Dis/dsx1B8ZS	0-110 ft	LocalTim		

www.cisco.com

Network Interface Switched WAN (Cont.)

Display Line Detail

MGX1.1.7.FRSM.a > dspln 1

LineNum:	1
LineConnectorType:	DB-15
LineType:	dsx1ESF
LineEnable:	Modify
LineCoding:	dsx1B8ZS
LineLength:	0-110 ft
LineXmtClockSource:	LocalTiming
LineLoopbackCommand:	LocalLineLoop
LineSendCode:	NoCode
LineUsedTimeslotsBitMap:	0x7
ConfigChangePortBitMap:	0x0

www.cisco.com


Network Interfaces Switched WAN Frame Relay

- **Frame Relay ports**
 - Serial**
 - Fractional**
 - Channelized**

www.cisco.com

Network Interfaces Switched WAN Frame Relay (Cont.)


Frame Relay Service Module



www.cisco.com

Network Interfaces Switched WAN Frame Relay (Cont.)


Serial Frame Relay Ports



www.cisco.com

Network Interfaces Switched WAN Frame Relay (Cont.)


Fractional Frame Relay Ports



www.cisco.com

Network Interfaces Switched WAN Frame Relay (Cont.)

Channelized Frame Relay Ports



www.cisco.com

Network Interfaces Switched WAN Frame Relay (Cont.)

Display Frame Relay Ports

MGX1.1.5.FRSM.a > dspport 1

```
SlotNum: 5
PortLineNum: 1
PortNum: 1
PortRowStatus: Mod
PortDs0Speed: 64k
PortDs0ConfigBitMap(1stDS0): 0x2(2)
PortQueueServiceRatio: 1
PortFlagsBetweenFrames: 1
PortSpeed: 64kbps
SignallingProtocolType: NoSignalling
AsynchronousUpdates: Disable
T391LineIntegrityTimer: 10
T392PollingVerificationTimer: 15
N391FullStatusPollingCounter: 6
N392ErrorThreshold: 3
N393MonitoredEventCount: 4
EnhancedLmi: Off
PortState: Active
PortSignallingState: No Signalling Failure
CLLMEnableStatus: Disable
CLLMxmtStatusTimer: 0
```

```
portType: frameRelay
PortIngrPercentUtil: 165
PortEgrPercentUtil: 165
PortOversubscribed: True
PortSvcStatus: Disable
PortSvcInUse: Not In-Use
PortSvcShareLcn: Card-based
PortSvcLcnLow: 0
PortSvcLcnHigh: 0
PortSvcDlciLow: 0
PortSvcDlciHigh: 0

PortDs0UsedLine1: 0x00000003
PortDs0UsedLine2: 0x00010001
PortDs0UsedLine3: 0x00010001
PortDs0UsedLine4: 0x00010001
PortNumNextAvailable: 41
```

Type <CR> to continue, Q<CR> to stop:

www.cisco.com

Network Interfaces Switched WAN Frame Relay (Cont.)

Display Frame Relay Port Counters

MGX1.1.5.FRSM.a > dspportcnt 1

PortNum:	1	
	Tx	Rx
Total Frames:	2265	692
Total Bytes:	1544730	63489
Frames FECN:	12	55
Frames BECN:	62	7
Frames Abort:	0	0
Buf Not Available:	0	0
KbpsAIR:	274	17
XmtFramesDiscXceedQDepth:	3	
XmtBytesDiscXceedQDepth:	192	
XmtFramesDuringLMIAlarm:	0	
XmtByteDuringLMIAlarm:	0	
XmtFramesUnderrun:	1	
RcvFramesDE:		0
RcvFramesDiscCRCError:		0
RcvFramesDiscIllegalHeader:		0
RcvFramesDiscAlignmentError:		0
RcvFramesDiscIllegalLen:		0

www.cisco.com

Network Interfaces Switched WAN Frame Relay (Cont.)

Display Frame Relay Port Counters

	Tx	Rx
RcvFramesDiscXceedDEThresh:		
RcvFramesUnknownDLCI:		0
RcvLastUnknownDLCI:		0
RcvFramesTaggedFECN:		6
RcvFramesTaggedBECN:		0
RcvFramesTaggedDE:		0
Status:	982	0
StatusInquiry:	0	981
AsynchUpdate:	5	0
RcvInvalidRequest:		0
RcvUNISeqMismatch:		0
RcvNNISeqMismatch:		2
UNISignallingTimeout:		0
NNISignallingTimeout:		0
FramesCLLM:	0	0
BytesCLLM:	0	0
CLLMFailures:		0

www.cisco.com

Network Interfaces Switched WAN Frame Relay (Cont.)

Display Frame Relay Channel Counters

```
MGX1.1.5.FRSM.a > dspchancnt 16
```

ChanNum:	16		
ChanState:	alarm		
ChanUpTime:	31		
		Tx	Rx
AbitState:	Sending A=1		Off
ATMState:	Sending AIS OAM state		Not receiving any state
Total Frames:	541		105
Total Bytes:	324059		9345
Frames DE:	0		0
Bytes DE:	0		0
Frames Discarded:	0		0
Bytes Discarded:	0		0
FramesDiscXceedQDepth:	0		0
BytesDiscXceedQDepth:	0		0
FramesDiscXceedDEThresh:	0		0
Frames FECN:	0		0
Frames BECN:	0		0
FramesTagged FECN:	3		0
FramesTagged BECN:	0		8
KbpsAIR:	142		9

www.cisco.com

Network Interfaces Switched WAN Frame Relay (Cont.)


Display Frame Relay Channel Counters

	Tx	Rx
FramesTaggedDE:	0	2
BytesTaggedDE:	0	89
RcvFramesDiscShelfAlarm:		0
XmtFramesDiscPhyLayerFail:	0	
XmtFramesDiscCRCError:	0	
XmtFramesDiscReAssmFail:	0	
XmtFramesDiscSrcAbort:	0	
XmtFramesDuringLMIAlarm:	18	
XmtBytesDuringLMIAlarm:	3330	
RcvFramesDiscUPC:		0
XmtFramesInvalidCPIs:	0	
XmtFramesLengthViolations:	0	
XmtFramesOversizedSDUs:	0	
XmtFramesUnknownProtocols:	0	
RcvFramesUnknownProtocols:		0

www.cisco.com


Network Interfaces Switched WAN ATM

ATM UNI Service Module



www.cisco.com

AUSM—8T1/E1 ATM Ports



www.cisco.com

Network Interfaces Switched WAN ATM

Display ATM Ports

```
MGX1.1.6.AUSM8.a > dspport 1
```

LogicalPortNumber:	1
Port Enable:	UP
Port State:	Active
PortType:	UNI
PhysicalPortNumber:	1
CellFraming:	ATM
CellScramble:	No Scramble
Ppp Loopback:	No Loopback
Single-bit error correction:	Disabled

www.cisco.com

Network Interfaces Switched WAN ATM (Cont.)


Display ATM Port Counters

```
axe1.1.6.AUSM8.a > dspportcnt 1
```

PortNum:	1
PortState:	Active
IngressRcvCells:	32
IngressGFCErrCells:	0
IngressVpiVciErrCells:	0
IngressUnknownVpiVci:	0x0
EgressXmtCells:	32
EgressPortAlarmDiscardCells:	0
EgressXmtClpSetCells:	0
EgressXmtErciSetCells:	0
PortXmtAisCells:	32
PortXmtSgmtLpbkCells:	0
PortRcvAisCells:	32
PortRcvFerbCells:	0
PortRcvSgmtLpbkCells:	0
PortRcvCrcErrOAMCells:	0
ReceivedHECErrCells:	0
HECErroredSeconds:	0
SeverelyHECErroredSeconds:	0

www.cisco.com

MGX ATM Connection



www.cisco.com

Network Interfaces Switched WAN ATM (Cont.)

Display ATM Channel Counters

MGX1.1.6.AUSM8.a > dspchanct 16

ChanNum:	16
ChannelState:	Alarm
ChannelEgressRcvState:	Alarm
ChannelEgressXmitState:	Sending OAM AIS
ChannIngressRcvState:	Receiving AIS
ChannIngressXmtState:	Sending OAM AIS
ChanInServiceSeconds:	4
ChanIngressPeakQDepth(cells):	0
ChanIngressReceiveCells:	0
ChanIngressClpSetCells:	0
ChanIngressEfcSetRcvCells:	0
ChanIngressUpclpSetCells:	0
ChanIngressQfullDiscardCells:	0
ChanIngressClpSetDiscardCells:	0
ChanIngressTransmitCells:	0
ChanShelfAlarmDiscardCells:	0
ChanEarlyPacketDiscardCells:	0
ChanPartialPacketDiscardCells:	0

www.cisco.com

Network Interfaces Switched WAN ATM (Cont.)

Display ILMI Counters

MGX1.1.6.AUSM8.a > dspilmicnt 1

PortNum:	1
SNMPPDUsReceived:	12
GetRequestReceived:	10
GetNextRequestReceived:	0
SetRequestReceived:	0
TrapReceived:	0
GetResponseReceived:	2
GetResponseTransmitted:	9
GetRequestTransmitted:	3
TrapsTransmitted:	4
InvalidPDURceived:	0
Asn1ParseError:	0
NoSuchNameError:	0
TooBigError:	0

www.cisco.com

Network Interfaces Switched WAN ATM (Cont.)

Display ATM Channel

MGX1.1.6.AUSM8.a > dspchan 16

ChanNum:	16
RowStatus:	Add
ConnectionType:	VCC
ServiceType:	UBR
PortNum:	1
VPI:	40
VCI (For VCC):	40
Local VPIId(for VPC):	0
EgressQNum:	4
IngressQDepth(cells):	1000
IngressDiscardOption:	CLP hysteresis
IngressFrameDiscardThreshold:	1000
IngressQCLPHigh(cells):	900
IngressQCLPLow(cells):	800
QCLPState:	LOW
IngressEfciThreshold(cells):	1000
UPCEnable:	Enabled
PeakCellRate[0+1](cells/sec):	3622
CellDelayVariation[0+1](in micro secs):	10000
PeakCellRate[0](cells/sec):	3622

www.cisco.com

Network Interfaces Switched WAN ATM (Cont.)


Display ATM Channel (Cont.)

CellDelayVariation[0](in micro secs):	250000
SustainedCellRate(cells/sec):	3622
MaximumBurstSize(cells):	1000
SCRPolicing:	CLP[0]
CLPTagEnable:	Enabled
FrameGCRAEnable:	Disable
ForesightEnable:	Disable
InitialBurstSize(cells):	0
ForeSightPeakCellRate(cells/sec):	3622
MinimumCellRate(cells/sec):	0
InitialCellRate(cells/sec):	0
LocalRemoteLpbkState:	Disable
ChanTestType:	No Test
ChanTestState:	Not In Progress
ChanRTDresult:	65535 ms
Ingress percentage util:	100
Egress percentage util :	0
Egress Service Rate:	0

www.cisco.com

Network Interfaces Switched Testing


Generic Loop Definition



www.cisco.com

Network Interfaces Switched Testing (Cont.)

BERT on the SRM



www.cisco.com

Network Interfaces Switched Testing (Cont.)

Local Loops

- Line or port
From SRM—Cnfbert
- Channel
From service module
Addchanloop—delchanloop

www.cisco.com

Network Interfaces Switched Testing Channel Loopback

```
MGX4.1.9.FRSM.a > addchanloop 16
SAR-MSG>>LCN 16 rcv loopback is enabled/disabled
MGX4.1.9.FRSM.a > dspchan 16
ChanNum:                16
ChanRowStatus:          Mod
ChanPortNum:            1
ChanMapVpi:             9
ChanMapVci:             16
ChanCBRSservice:        unstructured
ChanClockMode:          Synchronous
ChanCAS:                 Basic
ChanPartialFill:        0
ChanMaxBufSize:         564 bytes
ChanCDV:                 1000 micro seconds
CLIP:                   1000 milliseconds
ChanLocalRemoteLpbkState: Enabled
ChanTestType:           TestOff
ChanTestState:          NotInProgress
ChanRTDresult:          65535 ms
```

www.cisco.com

Network Interfaces Switched Testing (Cont.)

Remote Loops

- **Line**
FRSM and AUSM from SRM
Cnfbert
- **Port**
FRSM and AUSM from SRM
Cnfbert

www.cisco.com

Network Interfaces Switched Testing (Cont.)


Far-End Loops

- **Line or port**
- **SRM BERT**
- **Dependent on attached end-user equipment**

www.cisco.com

Network Interfaces Switched Testing (Cont.)

Configure BERT Menus



www.cisco.com

Network Interfaces Switched Testing (Cont.)

Display BERT Results

```
axe1.1.3.ASC.a > dspbert
```

```
User : test
Start Date : 04/14/98
Current Date : 04/14/98
Start Time : 18:08:42
Current Time : 18:08:54
Physical Slot Number : 5
Logical Slot Number : 5
Line Number : 1 (Line test)
DS0 Speed : 64K
Test Type : BERT Pattern Test
Device To Loop : No Loopback
BERT Pattern : All Zeroes Pattern
Error Inject Count : 0
Bit Count : 9075815
Bit Error Count : 0
Bit Error Rate (BER) : 0
```

BERT is in sync.

Note: You Must Use Delbert Command to End Test

www.cisco.com



**Please Complete Your
Evaluation Form**

Session 103

www.cisco.com

CISCO SYSTEMS



**EMPOWERING THE
INTERNET GENERATIONSM**

www.cisco.com